

## Information Notice

**NUMBER:** 600870-000032


**SUBJECT:** WIRELESS BLOCKAGE & FLOW MONITOR ACCESS POINT SSID RENAMING

**DATE:** 4/16/2019

This information notice describes how to change the SSID of your access point. This is likely to fix access point connection issues if no ECUs appear during WBFM configuration.

### SSID Re-naming Instructions

1. Ensure that your access point is powered on.
2. Connect to the IASBlockage or IASNetwork2 network through the iPad.
  - a. Tap the **Settings** icon on the iPad Home screen.
  - b. Tap **Wi-Fi** on the left navigation.
  - c. Tap **IASBlockage** or **IASNetwork2**.
3. Open an internet browser on your iPad.
4. Type *192.168.1.254* in the top navigation bar. Tap **Go**.
5. Enter the login information below. Tap **Login**.
  - User Name: *ias*
  - Password: *ias2200* (username and password are case sensitive)
6. Tap the **Wireless** tab on the top navigation.
7. Under **Wireless AP Settings**, type the new SSID in the **SSID** field.
  - If you have **white stickers** on your ECUs change the SSID to **IASBlockage**.
  - If you have **black stickers** on your ECUs change the SSID to **IASNetwork2**.



Wireless AP Settings

Wireless Radio:  Enable

SSID:   Enable SSID Broadcast

Security Mode:

RADIUS MAC Authentication:  Enable ?


Apply

Multi-SSID


Wireless MAC Filtering

Advanced Wireless Settings

8. Tap **Apply**, then tap **Save** at the top.



If you get an error message that says “Failed to get data”, toggle the **Wi-Fi** switch in the iPad settings. Then, open the browser again and refresh the page. Tap **Save** at the top.



9. Connect to the IASBlockage or IASNetwork2 network through the iPad.
  - a. Tap the **Settings** icon on the iPad Home screen.
  - b. Tap **Wi-Fi** on the left navigation.
  - c. Tap **IASBlockage** or **IASNetwork2** (whichever one you just changed the name to).
10. Open the Recon Blockage Monitor app. Tap the settings (gear) icon) and configure the system through the setup wizard.

## Contact

Questions? Contact your Intelligent Ag Support Specialist. If you don't have your Support Specialist's information, call our main office at +1-701-356-9222 or send an e-mail to [support@intelligentag.com](mailto:support@intelligentag.com).